

4TH SEM./ ELECTRICAL /2024(S)

Th-1 Energy Conversion-I

Full Marks: 80

Time- 3 Hrs

Answer any five Questions including Q No.1& 2
Figures in the right hand margin indicates marks

1. Answer **All** questions 2 x 10
 - a. Define ratio error in potential transformers.
 - b. What is the significance of back emf in DC motor running?
 - c. What is the role of Buchholz relay in transformer?
 - d. State the voltage equation of DC motor and also the condition for maximum mechanical power developed.
 - e. What are the two effects of the armature reaction in DC generator?
 - f. What is the working principle of a single phase transformer?
 - g. State two functions of yoke in DC machines.
 - h. What is the role of equalizer bar in DC series generators connected in parallel?
 - i. What is 'all day efficiency' in distribution transformers?
 - j. Why transformer rating is expressed in kVA?

2. Answer Any **Six** Questions 6 x 5
 - a. Describe the short circuit test on a single phase transformer with a neat diagram.
 - b. Determine the efficiency of DC machine by swinburne's test method.
 - c. Describe the external characteristics in DC shunt generator.
 - d. A 230 V dc shunt motor takes 5 A at no load and runs at 1000 rpm. Calculate the speed when loaded and taking a current of 30 A. The armature and field resistances are 0.2 ohm and 230 ohm respectively.
 - e. Explain the operation of ON Load Tap changer in transformer using resistor transition.
 - f. Write a short note on current transformer (CT).
 - g. In a 25 kVA, 2000/200 V transformer the iron and copper losses are 250 and 350 W respectively. Calculate the efficiency on UPF at half load.

- 3 A 200 KVA, 2000/440 V, 50Hz single phase Transformer gave the following Test Result : 10
O.C Test : 2000v, 1.8 A, 1.75KW on HV side
S. C Test : 13 V, 300 A, 1KW..... on LV side
Obtain the equivalent Circuit as referred to HV side.
- 4 A DC shunt generator has Full Load current of 196A at 220V. The stray losses are 720W and the shunt field coil resistance is 55 ohm. If it has a full load efficiency of 88%, find the armature resistance. Also find the load current corresponding to maximum efficiency. 10
- 5 Describe the process of commutation in DC Generator along with sketch diagram in details. 10
- 6 Describe the constructional features and working principle of single phase Auto Transformer. 10
- 7 A DC series motor drives a load the torque of which varies as the square of the speed. The motor takes a current of 15A when the speed is 600 rpm. Calculate the speed and the current when the motor field winding is shunted by a diverter of the same resistance as that of the field winding. Neglect armature, series winding and brush drops. 10